

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Transmission Control Module Read Only Memory	P0601	EPROM/Flash memory corruption (Incorrect program/calibrations checksum)	ROM fail count ≥ 5	None	Immediate Type A
Transmission Control Module Not Programmed	P0602	Non-programmed TCM (calibrations)	KbCOND_NoStartCal = TRUE	None	Immediate Type A
Transmission Control Module Long-Term Memory Reset	P0603	Wrong copy of Non-volatile Memory to RAM	Non-volatile memory (static or dynamic) checksum failure	None	Immediate Type A
Transmission Control Module Random Access Memory	P0604	RAM failure	RAM read/write failure (single word) RAM fail count ≥ 5	None	Immediate Type A
Powertrain Internal Control Module EEPROM Error	P062F	NVM write error at key-down	TCM Non-Volatile Memory Incorrect flag = 1	$8.0 \leq$ Ignition Voltage ≤ 18.0 V Ignition ON	Immediate Type A

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Trans Fluid Temp Sensor Circuit Range/ Performance	P0711	<p>The DTC detects the following failure modes of the TFT:</p> <p>1) A sensor that remains at a value. (Stuck Sensor)</p> <p>2) A sensor that remains at a value. (Stuck Sensor)</p> <p>4) Transmission Temperature remains below 20° C for a calibrated time dependant on startup transmission temperature.</p>	<p><u>Fail Case 1</u> $\Delta TFT < 2^{\circ}C$. TCC Slip ≥ 120 RPM for 300 sec cumul. $-39^{\circ}C \leq TFT$ at startup $\leq 20^{\circ}C$.</p> <p><u>Fail Case 2</u> $\Delta TFT < 2^{\circ}C$. $129^{\circ}C \leq TFT$ at startup $\leq 149^{\circ}C$.</p> <p><u>Fail Case 4</u> $TFT \leq 20^{\circ}C$ after a calibrated amount of time based on a 2D lookup table.</p>	<p><u>For fail case 1, 2, and 4:</u> Common ignition voltage enable, Common engine speed enable, No Engine Coolant DTC's, No OSS P0722, P0723 DTCs, No ISS P0716, P0717 DTCs, P0711 has not passed this ignition cycle, $-39^{\circ}C \leq$ trans fluid temp $\leq 149^{\circ}C$</p> <p><u>Fail case 1:</u> $-39^{\circ}C \leq$ trans fluid temp $\leq 20^{\circ}C$ at startup, Engine coolant $\geq 70^{\circ}C$, Engine Coolant has changed $\geq 55^{\circ}C$ since startup, Vehicle speed ≥ 8 kph for > 300 seconds (cumulative timer)</p> <p><u>Fail case 2:</u> $129^{\circ}C \leq$ trans fluid temp $\leq 149^{\circ}C$ at startup, Engine coolant $\geq 70^{\circ}C$ Engine Coolant has changed $\geq 55^{\circ}C$ since startup, Vehicle speed ≥ 8 kph for ≥ 300 seconds (cumulative timer)</p> <p><u>Fail case 4:</u> Valid TPS, Torque signal, and Crank Signals. $50 \text{ Nm} \leq$ Engine Torque $\leq 1492 \text{ Nm}$ $2\% \leq$ Throttle Position $\leq 90\%$ $8 \text{ kph} \leq$ Vehicle Speed $\leq 511 \text{ kph}$ $500 \text{ rpm} \leq$ Engine Speed $\leq 6500 \text{ rpm}$ $-39^{\circ}C \leq$ Coolant Temperature $\leq 149^{\circ}C$</p>	<p><u>Fail case 1:</u> 80.0 seconds Continuous</p> <p><u>Fail case 2:</u> 80.0 seconds Continuous</p> <p><u>Fail case 4:</u> Between 200 & 1900 seconds dependant on startup trans temperature. Continuous Type C-</p>
Transmission Fluid Temperature Sensor Circuit Low Voltage	P0712	Continuous Short-to-Ground in Trans Fluid Temperature sensor or TFT signal circuit	<p>Trans Temp Sensor ≤ 43.19 ohm</p> <p>Trans Temp $> 150C$</p>	<p>$8V \leq$ Ignition Voltage $\leq 18V$ for 5 sec $500 \leq$ Engine RPM ≤ 6500 for 5.0 sec</p>	<p>12.0 sec Continuous Type C-</p>
Transmission Fluid Temperature Sensor Circuit High Voltage	P0713	Continuous Open of Short to Voltage in Transmission Fluid Temperature sensor or TFT signal circuit	<p>Trans Temp Sensor ≥ 171862 ohm</p> <p>Trans Temp $< -40C$ (-40F)</p>	<p>No P0716, P0717, P0722, P0723 DTCs $500 \leq$ Engine RPM ≥ 6500 for 5.0 sec $8.0 \leq$ Ignition Voltage $\leq 18.0 V$ OSS ≥ 64.3.* RPM for 200 sec cumul. TCC Slip ≥ 120 RPM for 200 sec cumul.</p>	<p>80.0 sec Type C- Continuous</p>

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Input Speed Sensor Performance	P0716	0 – 6500 RPM Unrealistically large drop in Input Speed in a very period of time that remains	Input Speed drop \geq 1000 RPM	No P0717, P0722, P0723, P0752, P0973, P0974 DTCs 8V \leq Ignition Voltage \leq 18V 500 \leq Engine RPM \leq 6500 for 5 sec No TP malfunction No Engine Torque malfunction 50 \leq Engine Torque \leq 1492 N-m TPS \geq 8.0% Vehicle Speed \geq 16.0 kph ISS \geq 1050 RPM for 2.0 sec Δ ISS \leq 500 RPM for 2.0 sec	3.25 sec Type B Continuous
Input Speed Sensor Circuit Low Voltage	P0717	0 – 6500 RPM Low Input Speed with large vehicle speed	Input Speed $<$ 100.0 RPM	No P0717, P0722, P0723 DTCs No Engine Torque malfunction 500 \leq Engine RPM \leq 6500 for 5 sec 8V \leq Ignition Voltage \leq 18V Vehicle Speed \geq 16.0 kph 50 \leq Engine Torque \leq 1492 N-m	4.5 sec Continuous Type B
Output Speed Sensor Circuit Low Voltage	P0722	0 - 6500 RPM Low vehicle speed with large engine speed in Drive range	<u>Drive</u> 50 \leq Engine Torque \leq 1492 N-m Output Speed \leq 64.3* RPM <u>Park/Neutral</u> 1492 \leq Engine Torque \leq 1492 N-m	No, P0716, P0717, P0723 No TPS malfunction No Engine Torque malfunction 8V \leq Ignition Voltage \leq 18V 500 \leq Engine RPM \leq 6500 for 5.0 sec Range \neq P/N TCC Slip \geq -20 RPM Trans Temp \geq -40° C. 1500 RPM \leq Input Speed \leq 6500 RPM TPS \geq 8.0%	4.5 sec Continuous Type B
Output Speed Sensor Circuit Intermittent	P0723	0 - 6500 RPM Loss of vehicle speed when vehicle is moving	Drop in Output Speed $>$ 385.8* RPM in any Drive range	No P0716, P0717, P0974 DTC 8V \leq Ignition Voltage \leq 18V 500 \leq Engine RPM \geq 6500 for 5 sec Range \neq P/N 50 Nm \leq Engine Torque \leq 1492 Nm Time since last range change \geq 6.0 sec $+\Delta$ VSS, loop-to-loop, \leq 160.8* RPM for 2.0 sec Δ ISS \leq 500 RPM for 2.0 sec Output Speed \geq 321.5* RPM for 2.0 sec	3.25 sec Continuous Type B

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Torque Converter Clutch System - Stuck Off	P0741	High TCC slip with TCC commanded on	TCC slip Error \geq 125 RPM Count = 2	No P0716, P0717, P0722, P0723, P0742 No TPS malfunction No Engine Torque and Speed malfunctions $8V \leq$ Ignition Voltage \leq 18V $500 \leq$ Engine RPM \leq 6500 for 5.0 sec $50 \leq$ Engine Torque \leq 1492 N-m $2.0\% \leq$ TPS \leq 90% $20^\circ C. \leq$ Trans Temp \leq 130° C. TCC Capacity \geq 65% for 2.0 sec Commanded Gear > 2 TCC Mode = On or Locked On	8 sec Continuous Type B
Torque Converter Clutch System - Stuck On	P0742	Low TCC slip with TCC commanded off	-20 rpm \leq TCC Slip Speed \leq 40 rpm Count = 4	No P0716, P0717, P0722, P0723, P0741 No TPS malfunction No Engine Torque and Speed malfunctions $8V \leq$ Ignition Voltage \leq 18V $500 \leq$ Engine RPM \leq 6500 for 5.0 sec TCC commanded OFF $50 \leq$ Engine Torque \leq 1492 N-m $20^\circ C. \leq$ Trans Temp \leq 130° C. $8\% \leq$ TPS \leq 90% $16 \text{ kph} \leq$ VSS \leq 511 kph $1.07 \geq$ Gear Ratio \geq 0.6324	4.0 sec Type B Continuous
1-2 Shift Solenoid Valve Performance - No First or Fourth Gear	P0751	2-2-3-3 shift pattern	<u>Fail Case 1</u> Commanded 1st $1.5483 < \text{Ratio} < 1.7115$ <u>Fail Case 2</u> Commanded 4th $0.95 < \text{Ratio} < 1.05$ Count = 2	No P0716, P0717, P0722, P0723, P0742, P0973, P0974, P0976, P0977, or TPS DTCs (see below) No Engine Torque malfunction $500 \leq$ Engine RPM \leq 6500 for 5.0 sec $8V \leq$ Ignition Voltage \leq 18V TPS \geq 8.0% $20^\circ C. <$ Trans Temp $<$ 130° C. 1.0 sec. after gear change $150 \leq$ Input Speed \leq 6500 RPM $50 \leq$ Engine Torque \leq 1492 N-m Output Speed \geq 64.3* RPM	<u>Fail Case 1</u> 2.0 sec <u>Fail Case 2</u> 4.0 sec Continuous Type B
1-2 Shift Solenoid Valve Performance - No Second or Third Gear	P0752	1-1-4-4 shift pattern	<u>Fail Case 3</u> Commanded 2nd $2.8120 < \text{Ratio} < 3.1080$ <u>Fail Case 4</u> Commanded 3 rd $0.6458 < \text{Ratio} < 0.7137$ Count = 2	See P0751	<u>Fail Case 3</u> 2.0 sec <u>Fail Case 4</u> 3.0 sec Continuous Type B

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
2-3 Shift Solenoid Valve Performance - No First or Second Gear	P0756	4-3-3-4 shift pattern	<p><u>Fail Case 5</u> $-20 \leq \text{TCC Slip} \leq 8191 \text{ RPM}$ $\text{VSS} \geq 64.3^* \text{ RPM}$ Commanded 1st $0.6458 \leq \text{Ratio} \leq 0.7137$</p> <p><u>Fail Case 6</u> Commanded 2nd $0.95 \leq \text{Ratio} \leq 1.05$</p> <p>Count = 2</p>	See P0751	<p><u>Fail Case 5</u> 2.0 sec</p> <p><u>Fail Case 6</u> 3.0 sec</p> <p>Continuous Type A</p>
2-3 Shift Solenoid Valve Performance - No Third or Fourth Gear	P0757	1-2-2-1 shift pattern	<p><u>Fail Case 7</u> $50 \leq \text{Engine Torque} \leq 1492 \text{ N-m}$ Commanded 3rd $1.5483 < \text{Ratio} < 1.7115$</p> <p><u>Fail Case 8</u> $5 \leq \text{Engine Torque} \leq 1492 \text{ N-m}$ Commanded 4th $2.8120 < \text{Ratio} < 3.1080$</p> <p>Count = 2</p>	See P0751	<p><u>Fail Case 7</u> 2.0 sec</p> <p><u>Fail Case 8</u> 2.0 sec</p> <p>Continuous Type A</p>
1-2 Shift Solenoid Control Circuit Low Voltage	P0973	0 – 12 V Continuous Short-to-Ground OR Open in Shift Solenoid A or SSA circuit (ODM)	SSA ODM feedback circuit state \neq PCM commanded state	Ignition ON $8.0 \leq \text{Ignition Voltage} \leq 18.0 \text{ V}$	Fail count = 44 out of 50 (Time \approx 4.4 sec) Continuous Type B
1-2 Shift Solenoid Control Circuit High Voltage	P0974	0 – 12 V Continuous Short-to-Power in Shift Solenoid A or SSA circuit (ODM)	SSA ODM feedback circuit state \neq PCM commanded state	Ignition ON $8.0 \leq \text{Ignition Voltage} \leq 18.0 \text{ V}$	Fail count = 44 out of 50 (Time \approx 4.4 sec) Continuous Type B
2-3 Shift Solenoid Control Circuit Low Voltage	P0976	0 – 12 V Continuous Short-to-Ground OR Open in Shift Solenoid B or SSB circuit (ODM)	SSB ODM feedback circuit state \neq PCM commanded state	Ignition ON $8.0 \leq \text{Ignition Voltage} \leq 18.0 \text{ V}$	Fail count = 44 out of 50 (Time \approx 4.4 sec) Type A
2-3 Shift Solenoid Control Circuit High Voltage	P0977	0 – 12 V Continuous Short-to-Power in Shift Solenoid B or SSB circuit (ODM)	SSB ODM feedback circuit state \neq PCM commanded state	Ignition ON $8.0 \leq \text{Ignition Voltage} \leq 18.0 \text{ V}$	Fail count = 44 out of 50 (Time \approx 4.4 sec) Continuous Type A
Internal Mode Switch A Circuit Low Voltage	P1820	0 – 12 V IMS A Signal is Low in Park and Drive	IMS Input A = Low in Drive (Range = Transitional 1)	$8\text{V} \leq \text{Ignition Voltage} \leq 18\text{V}$ $500 \leq \text{Engine RPM} \leq 6500$ for 5.0 sec Has not passed this key cycle IMS Input A = Low in Park for 1 sec No Engine Torque Malfunction $50 \leq \text{Engine Torque} \leq 1492 \text{ N-m}$	8.0 sec Continuous Type B

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Internal Mode Switch B Circuit High Voltage	P1822	0 – 12 V IMS B Signal is High in Park and Drive	IMS Input B = High/Open in Drive (Range = Transitional ¹³)	8V ≤ Ignition Voltage ≤ 18V 500 < Engine RPM < 6500 for 5.0 sec Has not passed this key cycle IMS Input B = High in Park for 1 sec No Engine Torque Malfunction 50 ≤ Engine Torque < 1492 N-m	8.0 sec Continuous Type B
IMS Mode 'P' Ckt Low	P1823	0 – 12 V IMS P Signal is High in Park and Drive	IMS Input P = Low in Drive (Range = Transitional 8)	8V ≤ Ignition Voltage ≤ 18V 500 ≤ Engine RPM ≤ 6500 for 5.0 sec Has not passed this key cycle IMS Input P = Low in Park for 1 sec No Engine Torque Malfunction 50 ≤ Engine Torque ≤ 1492 N-m	8.0 sec Continuous Type B
Trans Internal Mode Switch Illegal Range	P1825	0 - 12V	Range is Illegal	8V ≤ Ignition Voltage ≤ 18V 500 ≤ Engine RPM ≤ 6500 for 5.0 sec	8.0 sec Continuous Type B
Internal Mode Switch C Circuit High Voltage	P1826	0 – 12 V IMS C Signal is High in Drive	IMS Input C = High/Open in Drive (Range = Transitional)	No P0722 or P0723 DTC's 8V ≤ Ignition Voltage ≤ 18V Has not passed this key cycle Engine Torque ≥ 50 Nm Vehicle Speed ≥ 16 kph 3.1672 ≥ Gear Ratio ≥ 2.7528 or 1.7441 ≥ Gear Ratio ≥ 1.5157 or 1.0699 ≥ Gear Ratio ≥ 0.9301 or 0.7275 ≥ Gear Ratio ≥ 0.6324	8.0 sec Continuous Type B
Internal Mode Switch Does Not Indicate P/N During Start	P1915	0 – 12 V	IMS Not Equal to Park/Neutral During Crank	6V ≤ Ignition Voltage ≤ 18V Engine Speed ≥ 450 rpm Crank Requested ≥ 2.5 sec	2.0 sec Continuous Type B
Ignition 1 Switch Circuit Low Voltage	P2534	Continuous Open/Short-to-Ground in TCM Ignition 1 Switch circuit	Every 25 msec, the FAIL counter is incremented if an open or a short to ground is detected	Engine running	Fail Counts ≥ 200 out of 220 Samples (Time ≈ 5 sec) Continuous Type A
Torque Converter Clutch Pressure Control Solenoid Control Circuit High Voltage	P2763	Continuous Short-to-Voltage in TCC PWM circuit	Every 100 msec, the FAIL counter is incremented if a short to voltage is detected	Ignition ON 8V ≤ Ignition Voltage ≤ 18V 500 ≤ Engine RPM ≤ 6500 for 5.0 sec TCC Commanded ON	Fail Count = 44 out of 50 (Time ≈ 4.4 sec) Continuous Type B

07 GRP13a_4T80E LD8_L37.doc

SENSED PARAMETER	FAULT CODE	ACCEPTABLE OPERATING RANGE AND RATIONALITY	PRIMARY MALF DETECTION PARAMETERS	SECONDARY PARAMETERS AND CONDITIONS	MONITORING TIME & DTC TYPE
Torque Converter Clutch Pressure Control Solenoid Control Circuit Low Voltage	P2764	Continuous Open/Short-to-Ground in TCC PWM circuit or TCC PWM solenoid	Every 100 msec, the FAIL counter is incremented if an open or a short to ground is detected	Ignition ON 8V ≤ Ignition Voltage ≤ 18V 500 ≤ Engine RPM ≤ 6500 for 5.0 sec	Fail Count = 44 out of 50 (Time ≈ 4.4 sec) Continuous Type B
Controller Area Network Bus Communication Error	U0073	TCM cannot communicate on the CAN Bus	GetCNDD_b_BusOffSt() = TRUE	Ignition ON 8V ≤ Ignition Voltage ≤ 18V for 5 seconds	Fail Count = 5 out of 5 (Time ≈ 5 sec) Continuous Type B
Lost Communications with Engine Control System	U0100	Communication between TCM & Engine Control System Lost	CAN Bus ECM Error flag = 1	Ignition ON 8V ≤ Ignition Voltage ≤ 18V for 5 seconds	Fail Count = 12 out of 12 (Time ≈ 12 sec) Continuous Type B