SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Vehicle Speed Sensor - Low input	P0502	0 RPM to 6000 RPM This DTC detects a low vehicle speed when the vehicle has a large engine speed in a drive gear range.	Output Speed < 150 rpm	- Gear Range is not Park/Neutral - No TPS high or low DTC's set - No Map Sensor DTC's set - No PSA DTC set - Vacuum: 0 to 105 KPA - No engine torque default - Engine Torque: 40 to 400 ft-lbs - Throttle Position > 12% - Engine Speed > 3000 RPM	3 seconds Continuous	DTC Type B
Vehicle Speed Sensor - Intermittent	P0503	0 RPM to 6000 RPM This DTC detects an unrealistic large drop in vehicle speed.	In P/N: Output Speed drop > 8192 RPM Not P/N: Output Speed drop >1300 RPM	- Time since last Gear Range Change > 6 Seconds - Engine Speed >450 rpm - No Output Speed rise > 600 rpm within 2 seconds - No PSA DTC set - Time since 4WDL State Change > 6 seconds	In park or neutral 409 seconds Not in park or neutral 3 seconds	DTC Type B
Trans Fluid Temp Sensor Circuit - Performance Test	P0711	0.24V to 5.0V The DTC detects an unrealistically large change in transmission temperature or a value which remains constant for a period of time in which a measurable amount of change is expected.	 1) Failure 1 is true for ≥ 409 seconds 2) Failure 2 happens ≥ 14 times in 7 seconds. 	- System Voltage: 10 and 18 volts - No VSS DTC's - Raw TTS counts: 10 to 251 - No DTC 1870 - Trans Temp at startup:	1) 409 seconds 2) 7 seconds continuous	DTC Type
Trans Fluid Temp Sensor Circuit - Low input (high temp)	P0712	0.24V to 5.0V The DTC detects a continuous short to ground in the TTS signal circuit or the TTS sensor	Raw TTS count < 10	- System Voltage: 10 to 18 volts - Ignition "on"	10 seconds Continuous	DTC Type C
Trans Fluid Temp. Sensor Circuit - High Input (Low temp)	P0713	0.24V to 5.0V The DTC detects a continuous open or short to high in the TTS signal circuit or the TTS sensor	Raw TTS counts > 250	- System Voltage: 10 to 18 volts - Ignition "on"	400 seconds Continuous	DTC Type C

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
TCC Enable Solenoid Electrical	P0740	OV to 12V This DTC detects a continuous open or short to ground in the TCC circuit or the TCC solenoid	Fail Counter > 43 Counts out of 50 Total Counts	- System Voltage: 10 to 18 volts - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff	Continuous	DTC Type B
TCC System Stuck OFF	P0741	This DTC detects high torque converter slip when the TCC is commanded on.	TCC slip > 130 RPM	Engine Speed > 450 rpm for 6 seconds and not in fuel cutoff -Gear Range is D2, D3, or D4 -No PSA DTC set - No TPS high or low DTC's - No VSS DTC's - No TCC Enable Sol. DTC's - No TCC Control Sol. DTC's - No TCC Stuck on P0742 DTC - No Range change within 6 sec - Trans temp.; 20 C to 150 C - Throttle Position: 20% to 99% - Gear ratio: 0.89 to 1.02 - TCC is commanded on for 5 seconds - TCC duty cycle >= 75%	20 seconds Continuous	DTC Type B
TCC System Stuck ON	P0742	This DTC detects low torque converter slip when the TCC is commanded off.	TCC Slip: -20 to +20 RPM Fail Counter >= 2	- Engine Speed > 450 rpm for 6 seconds and not in fuel cutoff - No Range change within 5 sec. - No TP high or low sensor DTC's - No VSS DTC's - No TCC Enable Sol. DTC's - No TCC Control Sol. DTC's - No PSA DTC set - No Engine Torque Default - Eng Torque: 50 to 400 ft-lbs - Vacuum: 0 to 105 kPa - Commanded Gear is not 1st - Gear Range is D4 - Trans temp.; 20 C to 130 C - Throttle Position: 17% to 45% - TCC is commanded off - Engine Speed: 1000 to 3000 rpm - Speed Ratio: 0.64 to 1.35 - Vehicle Speed: 15 to 50 mph	5 seconds Continuous	DTC Type B

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Shift Solenoid A Performance	P0751	This DTC detects abnormal shift patterns: Stuck OFF: 2-2-3-3 pattern	Fail Counter >= 2. The fail counter is incremented when the following fail cases are true: Stuck OFF: 1 and 2	General -Engine Speed > 450rpm for 5 seconds and not in fuel cutoff -Gear range is D4 -Ignition voltage: 10 to 18 volts -Transfer case ratio in 4wd low: 0.9 to 1.2 -Transfer case ratio in 4wd high: .6 to 2.85 -Transmission output speed >= 150 rpm -No TP high or low DTC's -No VSS low or intermittent DTC's -No Solenoid electrical DTC's -No PSA DTC set -Trans Temp.: 20 C to 130 C	Continuous	DTC Type B
				Fail Case 1 - 1st gear commanded >= 2.0 seconds - TPS >= 10% - Engine torque: 50 to 400 ft lbs - Modeled speed ratio >= 0.35 - Gear ratio: 1.2 to 1.8 Fail Case 2 - 4th gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 50 to 400 ft lbs - Modeled speed ratio >= 0.85 - Gear ratio: 0.95 to 1.15 gear - TCC commanded ON - TPS: 8% to 35%	Fail Case 1 0.5 seconds one time Fail Case 2 6.0 seconds one time	
				- TPS: 8% to 35% - Speed Ratio: 0.65 to 0.80 - TCC Slip: -20 to +50 rpm for > 4 sec		

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Shift Solenoid A Performance	P0752	This DTC detects abnormal shift patterns: Stuck ON: 1-1-4-4 pattern	Fail Counter >= 2 The fail counter is incremented when the following fail cases are true: Stuck ON: 1 and 2	General -Engine Speed > 450rpm for 5 seconds and not in fuel cutoff -Gear range is D4 -Ignition voltage: 10 to 18 volts -Transfer case ratio in 4wd low: 0.9 to 1.2 -Transfer case ratio in 4wd high: .6 to 2.85 -Transmission output speed >= 150 rpm -No TP high or low DTC's -No VSS low or intermittent DTC's -No DTC 742 -No PSA DTC set -Trans Temp.: 20 C to 130 C Fail Case 1 - 2nd gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 25 to 400 ft lbs - Modeled speed ratio >= 0.5 - Gear ratio: 3.0 to 3.3 Fail Case 2 - 3rd gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 50 to 400 ft lbs - Modeled speed ratio >= 0.5 - Gear ratio: 0.65 to 0.9	Fail Case 1 2.0 seconds one time Fail Case 2 3.0 seconds one time	DTC Type B
Shift Solenoid A Electrical	P0753	OV to 12V This DTC detects a continuous open or short to ground in the SSA circuit or the SSA solenoid	Fail Counter > 43 Counts out of 50 Total Counts	- System Voltage: 10 to 18 volts - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff	Continuous	DTC Type B

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Shift Solenoid B Performance	P0756	This DTC detects abnormal shift patterns: Stuck OFF: 4-3-3-4 pattern	Fail Counter >= 1 The fail counter is incremented when the following fail cases are true: Stuck OFF: 1 and 2	- Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - Gear Range is D4 -Ignition voltage: 10 to 18 volts -Transfer case ratio in 4wd low: 0.9 to 1.2 -Transfer case ratio in 4wd high: .6 to 2.85 -Transmission output speed >= 150 rpm - No TPS DTC's - No VSS DTC's - No vss DTC's - No solenoid electrical DTC's - No PSA DTC set - Trans Temp: 20 C to 130 C -Fail Case 1 - 1st gear commanded >= 2.0 seconds -Transmission output speed >= 200 rpm - TPS >= 10% - Engine torque: 50 to 400 ft lbs - TCC slip: -3000 to 200 rpm - Gear ratio: 0 to 1.4 -Fail Case 2 - 2nd gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 50 to 400 ft lbs - Modeled speed ratio >= 0.5 - Gear ratio: 0.9 to 1.2	Fail Case 1 1.0 seconds one time	DTC Type A
					2.0 seconds one time	

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Shift Solenoid B Performance	P0757	This DTC detects abnormal shift patterns: Stuck ON: 1-2-2-1 pattern	Fail Counter >= 1 The fail counter is incremented when the following fail cases are true: Stuck ON: 1 and 2	- Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - Gear Range is D4 -Ignition voltage: 10 to 18 volts -Transfer case ratio in 4wd low: 0.9 to 1.2 -Transfer case ratio in 4wd high: .6 to 2.85 -Transmission output speed >= 150 rpm - No TPS DTC's - No VSS DTC's - No Solenoid electrical DTC's - No TCC Stuck On DTC No PSA DTC set - Trans Temp: 20 C to 130 C Fail Case 1 - 3rd gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 50 to 400 ft lbs - Modeled speed ratio >= 0.5 - Gear ratio: 1.6 to 1.8 Fail Case 2 - 4th gear commanded >= 1.0 seconds - TPS >= 10% - Engine torque: 0 to 400 ft lbs - Modeled speed ratio >= 0.5 - Gear ratio: 1.3 to 1.8	Fail Case 1 2.0 seconds one time Fail Case 2 2.0 seconds one time	DTC Type A
Shift Solenoid B Electrical	P0758	OV to 12V This DTC detects a continuous open or short to ground in the SSB circuit or the SSB solenoid	Fail Counter > 43 Counts out of 50 Total Counts	- System Voltage: 10 to 18volts - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff	Continuous	DTC Type A
3-2 Downshift Solenoid Electrical	P0785	OV to 12V This DTC detects a continuous open or short to ground in the SSB circuit or the SSB solenoid	Fail Counter > 43 Counts out of 50 Total Counts	- System Voltage: 10 to 18 volts - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff	Continuous	DTC Type B

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
PSA Circuit Malfunction	P1810	0V to 12V This DTC detects an invalid state of the PSA sensor or the PSA circuit by deciphering the PSA inputs.	Fail Case 1 Illegal Trans Pressure Switch State (111) or (101) Fail Case 2 Gear range is D2, D4, or Reverse during engine startup. Fail Case 3 Gear range is Park or Neutral when	Fail Case 1 - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - System Voltage: 10 to 18 volts Fail Case 2 - System Voltage: 10 to 18 volts - No VSS DTC's - Vehicle Speed <2 mph 1. Engine Speed < 80 rpm for > 0.1 seconds, then, 2. Engine Speed: 80 to 550 rpm for > 0.07 seconds, then,	Fail Case 1 60 seconds Fail Case 2 5 Seconds Fail Case 3 10 seconds Continuous	DTC Type B
			operating in D4.	3. Engine Speed > 550 rpm Fail Case 3 - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - System Voltage: 10 to 18 volts - 4th gear commanded - No Engine Torque Default - Engine Torque: 40 to 400 ft-lbs - Vacuum: 0 to 105 kPa - TCC Locked On - No VSS DTC's - Speed Ratio: 0.60 to 0.75` - TPS: 10% to 50%		
TCC PWM Solenoid Electrical	P1860	OV to 12V This DTC detects a continuous open or short to ground in the TCC PWM circuit or the TCC PWM sensor	Fail Counter > 43 Counts out of 50 Total Counts	- System Voltage: 10 to 18 volts - Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - Commanded Gear is 1st - TCC Duty Cycle <= 10% or >= 90%	Continuous	DTC Type B

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Transmission Component Slipping	P1870	This DTC detects excessive TCC slip when the torque converter clutch should be engaged.	If TCC slip is: 130 to 800 rpm for 7 seconds, then increment the Trans Slip Counter by one. When the counter reaches 3, set the code OR When fail case 2 is true.	- Engine Speed > 450 rpm for 5 seconds and not in fuel cutoff - Gear is not 1st - Gear Range is D4 - No PSA DTC's set - No TPS High or Low DTC's - No VSS DTC's - No solenoid electrical DTC's - Shift Solenoid Performance Diagnostic counters are all zero - TPS: 20% to 99% - Trans temp.: 20 C to 150C - No Engine Torque Default - Engine Torque: 50 to 400 ft-lbs - Vac: 0 to 105 kPa - Speed ratio: 0.69 to 0.88 - Engine Speed: 1500 to 3000 rpm - Vehicle Speed: 30 to 82 mph Fail Case 1 - TCC commanded on for > 5 sec - TCC duty cycle >= 40% for >= 5 seconds Fail Case 2 - Run fail case 2 immediately after fail case 1 increments the trans slip counter to either 1or 2. Discontinue fail case 2 if the TCC is commanded OFF at any time TPS: 20% to 99% Criteria A If: 130 rpm < TCC slip < 800 rpm for 7 seconds, then: Go to max pressure freeze adapts go to criteria B Criteria B If: 130 rpm < TCC slip < 800 rpm for 7 seconds, then: Command TCC OFF for 1.5 seconds go to criteria C Criteria C If: 130 rpm < TCC slip < 800 rpm for 7 seconds, then: Command TCC OFF for 1.5 seconds	Continuous	DTC Type B

SENSED PARAMETER	FAULT CODE	MONITOR STRATEGY DESCRIPTION	MALFUNCTION CRITERIA AND THRESHOLD VALUE(S)	SECONDARY PARAMETERS AND ENABLE CONDITIONS	TIME LENGTH AND FREQUENCY	MIL ILLUMINATION TYPE
Four Wheel Drive Low Circuit Performance	P1875	OV to 12V This DTC detects a continuous open or short to ground in the Four Wheel Drive low Circuit	Stuck On Engine Spd Divided by Transfer Case Output Spd Ratio: 0.8 to 1.2 Stuck Off Engine Spd Divided by Transfer Case Output Spd Ratio: 2.5 to 2.9	- Engine Speed > 450 rpm for 5 seconds and not at fuel cut off - No TPS DTC's set - No PSA DTC's set - Gear Range is D4 - Shift Solenoid Performance Counters are zero - No VSS Low DTC's set - No TCC Enable Sol. DTC's set - No TCC Control Sol. DTC's set - No SSA Sol. DTC's set - No SSB Sol. DTC's set - No TCC DTC's set - No TCC DTC's set - Eng Torque: 40 to 400 ft lbs - VAC: 0 to 105 kPa - Trans Temp: 20C to 130C - Vehicle Speed > 7 MPH - TPS: 17% to 50% Stuck ON - 4wd Low switch in 4wd Low - Transfer case not in 4wd Low - TCC Slip: -3000 to -50 rpm Stuck OFF - 4wd Low switch not in 4wd Low - Transfer case is in 4wd Low - TCC ON - TCC Slip: 100 to 3000 rpm	Stuck ON: 5 Seconds 1 Occurrence Stuck OFF: 10 Seconds 1 Occurrence Continuous	DTC Type B